

# Xtend-2/FL (MM)

## 10Base-2/10Base-FL Converter (Multi-Mode)

---

PART NUMBER	DESCRIPTION
ETP-20118	10Base-2/FL Multi-Mode Converter

## Specifications

---

### Interface:

BNC Connector for 10Base-2 Thin Ethernet connection  
ST Connector for 10Base-FL Multi-Mode Fiber Optic Connection

### Cable Type:

RG-58 Cable for 10Base-2 Thin Ethernet  
62.5/125µm Multi-Mode Fiber Optic Cable for 10Base-FL

### Distance:

185 meter max. for RG-58 cable  
2,000 meter max. for fiber optic cable

### Protocol:

Baseband

### Standards:

IEEE 802.3 10Base-2 and 10Base-FL Ethernet

### Connection Switch:

2-Position; 10Base-2 switch on BNC side  
for Termination On/Off

### LEDs:

LMON, COL, XMT, POWER, RCV, JAB, LINK

### Temperature:

0° to 55°C (Standard Operating)

### Humidity:

10 to 90% (Non-condensing)

### Dimensions:

4.2"(L) x 2.2"(H) x 0.8"(D)

### Power Adapter:

9V DC Input, 1A

### EMI:

FCC Class A



908 Canada Court  
City of Industry, CA 91748 U.S.A.  
**Phone:** 626.964.7873 or 800.346.6668 **Fax:** 626.964.7880  
[www.unicomlink.com](http://www.unicomlink.com) e-mail: [info@unicomlink.com](mailto:info@unicomlink.com)